



Data line surge protection

Replacement instruction

Rev. 1.0 • English

Dantherm[®]
CONTROL YOUR CLIMATE

Der tages forbehold for trykfejl og ændringer
Dantherm can accept no responsibility for possible errors and changes
Irrtümer und Änderungen vorbehalten
Dantherm n'assume aucune responsabilité pour erreurs et modifications éventuelles


Replacement instruction

| | |
|---------------------|---|
| Introduction | This instruction 075137 covers the replacement of the data line surge protector Dantherm no.046397, Motorola no. 5166563A0, when replacing it, from the original, to an replacement type from Transtector |
| Preparation | Make sure you have appropriate hand tools available |
| Warning | Never do any maintenance and/or repair job with the power connected to the unit. |

Exchanging the unit

Placement

The data line surge protector is placed on the internal cabinet divider plate between the Motorola unit and the Dantherm Electronics.



Removal

| Step | Action |
|------|--|
| 1 | Remove both LAN cables |
| 2 | Remove the two screws holding the unit |
| 3 | Remove the old unit from the cabinet |

Preparation




Prior to installing the new unit, please acknowledge that you have all the following shown parts.



Continued overleaf


Exchanging the unit, *continued*

Mounting

| Step | Action | Illustration |
|------|--|--|
| 1 | Locate the self-locking fastener, and make sure it's open |  |
| 2 | Mount the self-locking fastener in the upper hole, by punching it through the metal plate from the right hand side of the cabinet towards the left. |  |
| 3 | Place the dataline surge protecting unit, over the plastic pin, on the left hand side, facing with the earth screw terminal upwards, and lock the fastener, by punching the centre pin. PIN |  |

Exchanging the unit, *continued*

Mounting, *continued*

| | | |
|---|--|--|
| 4 | Mount the cable with the screw, making sure, that you have serrated washers on both side, and the nut with another serrated washer on the right hand side. |  |
| 5 | Re-mount the LAN cables | |



075137

Dantherm Air Handling A/S

Marienlystvej 65

7800 Skive

Denmark

www.dantherm.com

service@dantherm.com

Dantherm[®]
CONTROL YOUR CLIMATE